

4K HDMI Switcher

HDMI Switcher

HDMI SWITCHER by Milestone is a device that allows consumer to share multiple HDMI devices such as computers, laptops, DVD player, DVR, camera, with single or multiple projector or monitor or LCD or Plasma, providing single or simultaneous displays having HDMI Ports. The features of the HDMI switcher can enable the device to act as a home entertainment box that can output up to 8 channel high quality audio signal for best audio effects.

Let it select automatically or have a control over it....

HDMI switcher selects last power on input signal and switches over automatically for the same input!!! You can select input from IR remote control or from the front panel of the switcher.

Features

- ARC function can be enabled or disabled
- Automatically last powered on source
- Front panel feather touch switch
- RS232C port for Control
- RF Remote (optional)
- Wired Key pad (optional)
- Scan mode & Manual mode also present
- In Auto mode whenever cable is inserted in Input Channel, that channel gets selected automatically.

Application

- Board room, Rental, Staging, monitoring, Video conf., Digital signage etc.



ML 201HD-ARC-4K



SPECIFICATIONS

- HDTV compatible
- Support CEC function
- HDMI out with ARC function
- 4Kx2K@60Hz. 4:2:0 & supports 3D format
- Compatible with DVI Input – Output
- Uses Equalization and re-clocking technology
- Built in IR Remote with IR Extender connector
- Operating Temperature: 5° to 55°
- Storage Temperature: -40 to 70°

Connections:

Input>

- 2 x HDMI standard female connector
- 1 x RS232 Port – D-9Female
- 1 x External Remote or Contact closer port – D-9Male

Output>

- 1 x HDMI (ARC Enabled) standard female connector
- 1 x 3.5mm Audio EP connector
- 1 x SPDIF
- 1 x Toslink

Power:

100-240V A.C. Adapter > 5V DC – 1.0Amp.

Size:

(h/w/d) =50mm x 120mm x 115mm

Packing:

1*Manual,1*Power Adapter,1*Switcher.

Applicable Product line.

Models:

- ML-401 HD-ARC-4K switcher
- ML-401 HDMI switcher
- ML-801 HDMI switcher
- ML-402 HDMI switcher
- ML-401104 HD-ARC-4K switcher
- ML-HD101 HDMI OVER CAT-5
- ML-HDVGAA – HDMI >> VGA AUDIO Scaler
- ML-VGAAHD – VGA AUDIO >> HDMI Scaler
- RF-4 RF remote controller for 4 channel switcher
- RF-8 RF remote controller for 8 channel switcher
- RF-16 RF remote controller for 16 channel switcher
- KY-4 4 channel wired Key pad controller
- KY-8 8 channel wired key pad controller
- ML-SCU1 serial control unit for RS232 port control
- ML-SU1 0-64 channel selection, (0-9 and enter key)



HDMI switcher application.