

# 120W – Public Address Amplifier



PA – 6120 FM / USB / MIC



IPI's Public Address Amplifier with Built in USB FM Tuner, 3 Microphone Input with Mic 1 as priority input, 1 Aux input, 120 Watt Power, **6 Zone with individual Stepped Volume Control.** Line out available to Daisy chain amplifiers or to Connect an active subwoofer. Brushed Aluminium anodised panel with aluminium Knobs offering a luxurious finish.

## Applications:

This unit can cater various needs of PA system and BGM setup like building or hotel BGM music system, Business Music systems in offices or banking sectors, BGM applications, Restaurant or coffee shops etc.

## Specifications:

- Frequency : 50Hz – 20Khz +/- 3db
- Mic Sensitivity : 0.5mV@ 600Ohm
- Aux Sensitivity : 100mV @ 220K ohm
- THD : < = 1% @ 1 KHz
- Output: 100V/70V, 8 Ohm, All 6 Zones @100V
- Signal to Noise ratio : 86 dB
- Tone : Bass 100Hz+/-10dB,  
Treble 10KHz+/- 10dB

## Features:

- USB Input x 1
- FM Radio In Built
- Front Panel Control
- FM Antenna Connector
- Volume Control for each Zone
- IR Remote Controller

## Inputs:

- 1 x 1/4 inch Phone Jack
- 1 x USB 2.0
- 1 x Aux in (2 RCA)

## Output:

- 1 x Line out ( 2 RCA)
- Screw terminal type Connector

## Power:

230 V / 50 Hz Ac, 24V DC

## Size:

(H/W/D) = 100mm X 480mm X 350mm

## Packing:

- 1\* PA-6120 Amplifier
- 1\* IR Remote Controller.